



HTA-TTA111VR-1



FEATURES

Active Video Receiver BNC Male To 2 screw terminal adapter. video transceivers provide a highly balanced mode of video transmission. Five-position distance range switch to adjust transmission distance up to 2 km, which is immune to interference from these, and other sources of noise. Cable requirement: UTP, AC24V/DC12V dual power

- Transmit a full motion color or monochrome video signal and data signal
- Five position distance range switch to adjust transmission a full motion monochrome video signal up to 2400 meters, color video signal up to 1500 meters
- System is integrated with alarm sensor (PIR, Magnetic, etc.) or data (Pan, Tilt, Zoom)
- Built in transient protection and ground lifting, damaging voltage spike problems are eliminated
- AC24V/DC12V dual power for HTA-TTA111VR-1 model
- Red LED: power on/off for HTA-TTA111VR-1 model
- Power supply included

Specifications